
**magnetic circuit**

	a (mm)	Ø (mm)
CM 51	50	18.8

Nota: Utilisation of circuits  
CM 51: CBC 57-80 unipolar

**closing coils CM 51****circuit not power-saved****specification number: 366 450**

voltage in Volt 		to be used on network with normal voltage	Lenoir code	Brisch nr	Alsthom nr
mini.	maxi.				
5.6	7.3	6	95 001	39 010 889	368 855
7	9.2		95 002	39 010 890	368 856
8.9	11.6		95 003	39 010 891	368 857
11.4	14.8	12	95 004	39 010 892	368 858
12.7	16		95 005	39 010 893	368 859
14	18.5		95 006	39 010 894	368 860
18.2	23.2	24	95 007	39 010 895	368 861
22	28.6		95 008	39 010 896	368 862
28.5	36.5		95 009	39 010 897	368 863
34	45	48	95 010	39 010 898	368 864
45	56		95 011	39 010 899	368 865
50	63		95 012	39 010 900	368 866
58	72	110	95 013	39 010 901	368 867
73	92		95 014	39 010 902	368 868
91	111		95 015	38 436 181	366 454
115	141	115-125	95 016	38 436 182	366 455
141	172		95 017	39 010 903	368 869
178	214		95 018	39 010 904	368 870
203	247	220-230	95 019	38 436 183	366 456
235	282		95 020	39 010 905	368 871
320	382		95 021	39 010 906	368 872